# Installation Manual ALT-ST20-D360 POCKET DOOR SYSTEM (INSET) SOFT CLOSING

Thank you for selecting our product. Before starting installation, please read this manual thoroughly to ensure correct installation. Please keep this manual at hand for future reference.


### ABOUT THE PRODUCT

- This product is hardware for vertical pocket doors in furniture, enabling slow door closing.
- The door is stored inside the cabinet.
- The door incline can be easily adjusted via a 5-stage angle retention mechanism.



### SPECIFICATION

Туре	S	М	L	LL		
Rail Q'ty	2	3	4	4		
Door Width	Max. 600 mm					
Door Height	800 - 1200 mm	1200 - 1600 mm	1600 - 2000 mm	2000 - 2400 mm		
Door Thickness	18 - 30 mm					
Door Weight	Max. 9 kg	Max. 15 kg	Max. 20 kg	Max. 20 kg		



### FOR YOUR SAFETY AND CORRECT INSTALLATION



Prohibited

### Required

#### Caution If not followed, injury or damage may result.

- Provide a cabinet that can withstand the weight and impact of opening and closing the door. Be sure to use the specified screws and tighten them securely. If the mounting strength is insufficient, the door may fall and cause injury.
- Follow the specified dimensions, specifications, and alignment of the cabinet. Make sure that the cabinet is not warped, since it may affect the movement of the door.
- Position the handle so that the hand holding the handle does not strike the side board.
- When moving the cabinet, remove the door and re-assemble it at the site.
- This product is a part for furniture. After installation, check the function and safety of the final product.
- Make sure to check the screws for slack at regular intervals. (one month and six months from first usage and then once every year is recommended).
- Be sure to inform users of the precautions below regarding opening and closing.



- Do not force the door to open past 90°. Damage may result.
- Ŏ
- When closing the door, pull it out until the catch clicks and then close it.
- Repeated opening and closing may cause the inner rail to come off, shortening the door movement distance. Push the door fully inward or pull it fully out to correct the deviation.






### **COMPONENT PARTS/QUANTITY**


					Inset (ST20-D360)			
					<b>S</b> Туре	М Туре	<b>L</b> Туре	LL Type
1	Rail % <sup>1</sup>			AL127C 16 - 28 inches	2	3	4	4
2	Connecting plate	Connecting plate		ALT-ST20-S ALT-ST20-M ALT-ST20-L ALT-ST20-LL	1	1	1	1
	Cont	Adjustment bracket		ALT-ST20-LP	1	1	1	1
3	Concea	aled hinge		H360-D26-0T	2	3	4	5
4	Hinge mounting plate			§ 360-P4W-30T	2	3	4	5
5	Mounting plate		• •	ALT-MP30	2	3	4	5
6	Guide r	roller	P	ALT-GR	2	3	3	3
7	Catch	<sup>2</sup>	See	AL127-CH	2	2	3	3
8	Roller		٩	DU19-B4SBR	2	2	2	2
9	Roller bracket			ALT-2V-AB	1	1	1	1
			66	ALT-2V-BB	1	1	1	1
10	Insert r	nut	8	SC-107-13	2	2	2	2
1)	Slider		Q	G-175	2	2	2	2
(12)	ALT-AB M5 Adjustment bolt				1	2	2	2
(13)	Bind he	Bind head tapping screw 3.5×15			18	27	34	34
14	Bind head tapping screw 4×16			6	6	6	6	
(15)	Raised countersunk head tapping screw 3.5×15			4	6	8	10	
(16)	Hexagon flange head screw M4×6			10	15	20	20	
17	Raised	Raised countersunk head screw M4×10			6	9	12	15
(18)	Hex key			1	1	1	1	

 $^{*1}$  Do not cut rails. Rail sizes (inches) include 16, 19, 22, 24, and 28.  $^{*2}$  This catch holds the door at the pulled-out position. Be sure to mount it on the uppermost and lower slide rails



# DIMENSIONS: INSET \*Description is for left-handed product.


Rail Size	Door Storing	Cabinet Depth		
16	269 + Door Thickness	412 + Door Thickness		
19	345 + Door Thickness	488 + Door Thickness		
22	421 + Door Thickness	564 + Door Thickness		
24	472 + Door Thickness	615 + Door Thickness		
28	574 + Door Thickness	717 + Door Thickness		




### Mounting the insert nut, roller, and slider

Fixed on the top and bottom boards Fixed on the side board <Use roller bracket (9)> <Use insert nut 10> 8 Roller (1) Bind head tapping 10 Insert nut 1 Bind head tapping screw 4×16 (\$10 depth 13) screw 4×16 (8) Roller 1) Slider (\$ depth 10) 1) Slider ⑧ Roller 1) Slider (¢3 depth 10) Side mount bracket (Optional) In the second \*Mount symmetrically on the top board as well.


### 2 Mounting the concealed hinge, hinge mounting plate, mounting plate, and slider




**3** Temporarily fastening the slide rail and mounting the guide roller




## 4 Temporarily fastening connecting plates



### 5 Rail fixing



6 Hanging door Push the hinge into the hinge mounting plate




How to remove




Co

### 7 Adjusting the door





### 8 Door depth, vertical, horizontal, and closing speed adjustment



SUGATSUNE KOGYO CO., LTD. Tokyo, JAPAN Phone: +81 3 3866 2260 E-mail:export@sugatsune.co.jp SUGATSUNE KOGYO (UK) LIMITED Reading, UK Phone: +44 1189 272 955 E-mail:sales@sugatsune.co.uk SUGATSUNE EUROPE GmbH Dusseldorf, GERMANY Phone: +49 211 53812 900 E-mail:sales@sugatsune.eu SUGATSUNE AMERICA, INC. California, USA Phone: +1 310 329 6373 E-mail:sales@sugatsune.com Chicago, USA Phone: +1 630 317 7072 E-mail:sales@sugatsune.com

SUGATSUNE CANADA, INC. Montreal, CANADA Phone: +1 514 312 5267 E-mail:support@sugatsune.ca SUGATSUNE SHANGHAI CO., LTD. Shanghai, CHINA Phone: +66 21 3632 1858 E-mail:lamp@sugatsune.com.cn Guangzhou, CHINA Phone: +66 20 6639 3554 E-mail:lamp@sugatsune.com.cn

SUGATSUNE KOREA CO., LTD. Incheon, KOREA Phone: +82 32 220 0603 E-mail:sales@sugatsune-korea.co.kr 
 SUGATSUNE KOGYO INDIA

 PRIVATE LIMITED

 Mumbai, INDIA

 Phone: +91 9867299597

 E-mail:sales@sugatsune.in

 Delhi, INDIA

 Phone: +91 9867299597

 +91 114 45093636

 E-mail:sales@sugatsune.in

ISO9001(Japan Offices and Sugatsune America) and ISO14001(Chiba Production division and Logistics center), certified.

2023.05 1542-2